



Construction ■ Farm ■ Lawn ■ Sales ■ Service

Dixon Mowers

Maintenance	Daily		Weekly	Annually	Maintenance interval in hours			
	Before	After			25	50	100	300
Check the parking brake	*							
Check the engine's oil level	*							
Check the safety system	*							
Check for fuel and oil leakages	*							
Check/clean the engine's cooling air intake		*						
Check the mower deck		*						
Check for loose hardware (screws, nuts)		*						
Clean under the mower deck		*						
Start the engine and blades, listen for unusual sounds		*						
Check for damage		*						
Thoroughly clean around the engine		*						
Clean around belts, belt pulley's		*						
Check the tire pressures					*			
Check battery					*			
Sharpen/Replace mower blades					*			
Clean the engine's cooling air intake				*	*			
Clean the air cleaner's pre-filter				*	*			
Clean the air cleaner's filter cartridge				*		*		
Check/adjust the parking brake				*		*		
Inspect muffler/spark arrester				*		*		
Check/adjust throttle cable							*	
Check the condition of belts, belt pulleys				*			*	
Change the engine oil				*		*		
Replace the engine oil filter				*			*	
Clean/replace the spark plugs				*			*	
Replace the fuel filter				*			*	
Replace the air filter (paper filter)				*			*	
Check the caster wheels (200 hrs)							*	
Replace the air-cleaner's pre-filter				*				
Check/adjust the mower deck				*				*
Check the engine valve clearance				*				*
Perform the 300-hour service				*				*
Check hydraulic oil at reservoir			*					
Change hydraulic oil & filter (200 hr)				*				
Clean fins of oil cooler (Kohler)				*				*

B & K Power Equipment, Inc. Phone : (815) 923-4547
 17009 Harmony Road Fax : (815) 923-2043
 Marengo, IL 60152 info@bandkpower.com